



# Thermocouple TC-K Sensor

0 °C to 1200 °C

Product Number: ENTMP025



## Overview

The Thermocouple Type K (TC-K) sensor is a high temperature sensor with a range of 0°C to 1200 °C. It is extremely accurate and boasts a rapid response time.

The TC-K sensor is mainly used for high temperature measurements, monitoring chemical reactions that occur in high temperatures or even measuring ovens. The high accuracy and reliability of this sensor makes it an excellent tool for advanced Chemistry experiments.

The Temperature TC-K sensor can be connected to all types of einstein™ data loggers.

## Typical experiments



Chemistry

- Exploring the temperature of a candle flame
- Different boiling points of various solutions
- Melting points of certain solids

## How it works

A thermocouple consists of two long wires made of different metals connected at one end while at the other end they are close to each other but without making contact. When the connected end of the thermocouple is placed in a higher temperature than the unconnected end, voltage is produced between the wires. To correct for room temperature, another temperature sensor is built into the thermocouple. The adjusted voltage is then amplified and adjusted to a range of 0 - 3 V. The result is then displayed and recorded.

## Sensor specification

Range:	0 °C to 1200 °C 32 °F to 2192 °F 273.15 K to 1473.15 K
Accuracy:	±2 % over entire range
Resolution (12-bit):	0.3 °C 0.55 °F
Default Sample Rate:	10 samples per second

## Technical notes


- Recommended Sensor Usage: Resistant to mild chemical solutions
- Do not place the sensor's cable in liquid

## Data logging and analysis

### Android

1. Take your einstein™ Tablet OR pair your einstein™ LabMate with your Android or iOS tablet via Bluetooth
2. Insert the sensor cable into one of the sensor ports
3. Launch MiLABEx and then tap on LAB start an Experiment


4. MiLABEx will automatically detect the sensor
5. Make sure the icon next to the sensor is checked to enable it for logging




6. You are ready to start an Experiment

## Desktop

1. Pair your einstein™ LabMate with your PC, MAC, or Linux machine via Bluetooth, or connect it via the USB cable (found in the einstein™ LabMate box).
2. Insert the sensor cable into one of the sensor ports
3. Launch MiLABEx and then click on LAB start an Experiment
4. MiLABEx will automatically detect the sensor and show it in the Current Setup Summary window



5. Click Full Setup, located at the bottom of the Current Setup Summary window to program the data logger's sample rate, number of samples, units of measurement, and other options



- Click the Run button on the main toolbar of the Launcher View to start logging

## Calibration

The Temperature TC-K sensor is shipped fully calibrated.

## An Example of using the Thermocouple Sensor

### Exploring a Flame

The heat of a flame is not uniform. Zones within a flame have differing temperatures. These zones can be mapped utilizing the thermocouple's high-sensitivity, fast reaction times and ability to withstand high temperatures.

The following graph shows the temperature in three different zones of the candle flame.



Figure 1: The temperature in three different zones of the candle flame

## Troubleshooting

If the Temperature Sensor isn't automatically recognized by MiLABEx, please contact Fourier Education's technical support.

## Technical support

For technical support, you can contact the Fourier Education's technical support team at: Web: [www.einsteinworld.com/support](http://www.einsteinworld.com/support)  
Email: [support@fourieredu.com](mailto:support@fourieredu.com)

## Copyright and Warranty

All standard Fourier Systems sensors carry a one (1) year warranty, which states that for a period of twelve months after the date of delivery to you, it will be substantially free from significant defects in materials and workmanship.

This warranty does not cover breakage of the product caused by misuse or abuse.

This warranty does not cover Fourier Systems consumables such as electrodes, batteries, EKG stickers, cuvettes and storage solutions or buffers.

ALBERT EINSTEIN and EINSTEIN are either trademarks or registered trademarks of The Hebrew University of Jerusalem. Represented exclusively by GreenLight. Official licensed merchandise. Website: [einstein.biz](http://einstein.biz)

©Fourier Systems Ltd. All rights reserved. Fourier Systems Ltd. logos and all other Fourier product or service names are registered trademarks or trademarks of Fourier Systems. All other registered trademarks or trademarks belong to their respective companies.